

MODE	Mode settings					
g-shift	F.14 ☐	F.124 ☐	F.1234 ☐	KEY.LP ☐	MyMp ^s ☐	HOME _r ^s ☐
f-shift	M.14 ☐	M.124 ☐	M.1234 ☐	MNU _p 1 ☐	MyMb ☐	HOME _b ☐
unshifted	SRESET	g.2Tp ☐	SH.4s ☐	fg.GR ☐	fg.LIM ☐	fg.FUL ☐
Page 3	F1	F2	F3	F4	F5	F6

Prev menu https://47calc.com/doc/C47/Menus/C47_Menu_MODE_page_2.pdf

Next menu https://47calc.com/doc/C47/Menus/C47_Menu_MODEL_page_1.pdf

Ref 1 https://47calc.com/doc/Application%20Notes/AN0028_C47_R47_JM_Configurability_Tour.pdf

Ref 2 https://47calc.com/doc/Application%20Notes/AN0015_C47_R47_JM_Write_and_Read_Setting_Groups.pdf

Level	Label	Type	FullName	Extended description	Category	Flag	Catalog	Default
Menu p3	MODE	MENU	Mode settings	System (mode settings) settings ; Info : MODE replaces R47 menu PREF ; Ref : https://47calc.com/doc/Application%20Notes/AN0028_C47_R47_JM_Configurability_To_ur.pdf	System		MODE	
F1	SRESET	Command	Safe reset f/g timers	Safe reset, then toggle ON/OFF the timing related user interface options: fg.FUL ☒ , g.2Tp ☒ , SH.4s ☐ , HOMEf ☒	User interface		SRESET	
F2	g.2Tp ☒	Setting	Double tap function keys	Switch on double tap function keys for g-shift ; not programmable - in PEM, use flag g.2Tp ; Info : Blocked for navigation FN-keys (arrows) in editors	User interface	g.2Tp	g.2Tp ☒	ON
F3	SH.4s ☐	Setting	Shift time-out of 4s	Switch on shift time-out of 4s ; not programmable - in PEM, use flag SH.4s ; Info : For layouts containing key [f/g] only	User interface	SH.4s	SH.4s ☐	OFF
F4	fg.GR ☐	Setting (pgm)	Menu f,g-highlighting Grey	Switch on menu f,g-highlighting grey	User interface	fg.GR	fg.GR ☐	OFF
F5	fg.LIM ☐	Setting (pgm)	Menu f,g-highlighting Limited	Switch on menu f,g-highlighting limited ; Info : fg.LIM and fg.FUL are linked (both cannot be ON at the same time)	User interface	fg.LIM	fg.LIM ☐	OFF
F6	fg.FUL ☒	Setting (pgm)	Menu f,g-highlighting Full	Switch on menu f,g-highlighting full ; Info : fg.FUL and fg.LIM are linked (both cannot be ON at the same time)	User interface	fg.FUL	fg.FUL ☒	ON
ff1	M.14 ☐	Setting (pgm)	Math keys skip f- and g-shift	Longpress control : Math keys skip f- and g-shift ; Info : 1. primaryNM : unshifted ; 4. longestpress : NOP ; Math keys are keys in row 2-4 except [E] and [←]	User interface			OFF
ff2	M.124 ☐	Setting (pgm)	Math keys skip g-shift	Longpress control : Math keys skip g-shift ; Info : 1. primaryNM : unshifted ; 2. longestpress : f-shift ; 4. longestpress : NOP ; Math keys are keys in row 2-4 except [E] and [←]	User interface			OFF
ff3	M.1234 ☐	Setting (pgm)	Math keys do full cycle	Longpress control : Math keys do full cycle ; Info : 1. primaryNM : unshifted ; 2. longestpress : f-shift ; 3. longerpress : g-shift ; 4. longestpress : NOP ; Math keys are keys in row 2-4 except [E] and [←]	User interface			ON
ff4	MNUp1 ☒	Setting (pgm)	Menu opens on p1	Switch on menu opens on p1	User interface	MNUp1	MNUp1 ☒	ON
ff5	MyMb ☒	Setting	MyMenu shown	Switch on MyMenu shown ; not programmable - in PEM, use flag MyMb ; Info : MyMb and HOMEb are linked (both cannot be ON at the same time ; applies when all menus are exited using EXIT	Customisation	MyMb	MyMb ☒	ON
ff6	HOMEb ☐	Setting	HOME menu shown	Switch on HOME menu shown ; not programmable - in PEM, use flag HOMEb ; Info : HOMEb and MyMb are linked (both cannot be ON at the same time ; applies when all menus are exited using EXIT	Customisation	HOMEb	HOMEb ☐	OFF
gf1	F.14 ☐	Setting (pgm)	Function keys skip f- and g-shift	Longpress control : Function keys skip f- and g-shift ; Info : 1. primaryNM : unshifted ; 4. longestpress : NOP	User interface			OFF
gf2	F.124 ☐	Setting (pgm)	Function keys skip g-shift	Longpress control : Function keys skip g-shift ; Info : 1. primaryNM : unshifted ; 2. longestpress : f-shift ; 4. longestpress : NOP	User interface			ON
gf3	F.1234 ☐	Setting (pgm)	Function keys do full cycle	Longpress control : Function keys do full cycle ; Info : 1. primaryNM : unshifted ; 2. longestpress : f-shift ; 3. longerpress : g-shift ; 4. longestpress : NOP	User interface			OFF
gf4	KEY.LP ☒	Setting	Longpress f and g shortcuts	Switch on longpress shortcuts for single shift keys ; not programmable - in PEM, use flag KEY.LP ; Info : KEY.LP pertains to R47v0 f/g layout and R47v2 f/g layout only and also enables longpress assignment to single shift keys	User interface	KEY.LP	KEY.LP ☒	ON
gf5	MyMf ☐	Setting	MyMenu f/g shortcut	Switch on MyMenu activated by triple and longerpress f/g-shift ; not programmable - in PEM, use flag MyMf ; Info : MyMf and HOMEf are linked (both cannot be ON at the same time ; MyMf pertains to layouts containing key [f/g] only and also enables longerpress assignment to this key	Customisation	MyMf	MyMf ☐	OFF
gf6	HOMEf ☒	Setting	HOME menu f/g shortcut	Switch on HOME menu activated by triple and longerpress f/g-shift ; not programmable - in PEM, use flag HOMEf ; Info : HOMEf and MyMf are linked (both cannot be ON at the same time ; HOMEf pertains to layouts containing key [f/g] only and also enables longerpress assignment to this key	Customisation	HOMEf	HOMEf ☒	ON