

PREF	Preferences					
g-shift	F.14 ☐	F.124 ☐	F.1234 ☐	KEY.LP ☐	MyMp ^s ☐	HOME _r ^s ☐
f-shift	M.14 ☐	M.124 ☐	M.1234 ☐	MNU _p 1 ☐	MyMb ☐	HOME _b ☐
unshifted	SRESET	g.2Tp ☐	SH.4s ☐	fg.GR ☐	fg.LIM ☐	fg.FUL ☐
Page 3	F1	F2	F3	F4	F5	F6

Prev menu https://47calc.com/doc/R47/Menus/R47v0_Menu_PREF_page_2.pdf

Next menu https://47calc.com/doc/R47/Menus/R47v0_Menu_Prefix_page_1.pdf

Ref 1 https://47calc.com/doc/Application%20Notes/AN0028_C47_R47_JM_Configurability_Tour.pdf

Ref 2 https://47calc.com/doc/Application%20Notes/AN0015_C47_R47_JM_Write_and_Read_Setting_Groups.pdf

Level	Label	Type	FullName	Extended description	Category	Flag	Catalog	Default
Menu p3	PREF	MENU	Preferences	System preferences ; replaces MODE ; Info : PREF replaces C47 menu MODE ; Ref : https://47calc.com/doc/Application%20Notes/AN0028_C47_R47_JM_Configurability_ToUr.pdf	System		PREF	
F1	SRESET	Command	Safe reset f/g timers	Safe reset, then toggle ON/OFF the timing related user interface options: fg.FUL  , g.2Tp  , SH.4s  , HOMEf 	User interface		SRESET	
F2	g.2Tp 	Setting	Double tap function keys	Switch on double tap function keys for g-shift ; not programmable - in PEM, use flag g.2Tp ; Info : Blocked for navigation FN-keys (arrows) in editors	User interface	g.2Tp	g.2Tp 	ON
F3	SH.4s 	Setting	Shift time-out of 4s	Switch on shift time-out of 4s ; not programmable - in PEM, use flag SH.4s ; Info : For layouts containing key [f/g] only	User interface	SH.4s	SH.4s 	OFF
F4	fg.GR 	Setting (pgm)	Menu f,g-highlighting Grey	Switch on menu f,g-highlighting grey	User interface	fg.GR	fg.GR 	OFF
F5	fg.LIM 	Setting (pgm)	Menu f,g-highlighting Limited	Switch on menu f,g-highlighting limited ; Info : fg.LIM and fg.FUL are linked (both cannot be ON at the same time)	User interface	fg.LIM	fg.LIM 	OFF
F6	fg.FUL 	Setting (pgm)	Menu f,g-highlighting Full	Switch on menu f,g-highlighting full ; Info : fg.FUL and fg.LIM are linked (both cannot be ON at the same time)	User interface	fg.FUL	fg.FUL 	ON
fF1	M.14 	Setting (pgm)	Math keys skip f- and g-shift	Longpress control : Math keys skip f- and g-shift ; Info : 1. primaryNM : unshifted ; 4. longestpress : NOP ; Math keys are keys in row 2-4 except [<f>], [<g>], [EEX] and [*]	User interface			OFF
fF2	M.124 	Setting (pgm)	Math keys skip g-shift	Longpress control : Math keys skip g-shift ; Info : 1. primaryNM : unshifted ; 2. longpress : f-shift ; 4. longestpress : NOP ; Math keys are keys in row 2-4 except [<f>], [<g>], [EEX] and [*]	User interface			OFF
fF3	M.1234 	Setting (pgm)	Math keys do full cycle	Longpress control : Math keys do full cycle ; Info : 1. primaryNM : unshifted ; 2. longpress : f-shift ; 3. longerpress : g-shift ; 4. longestpress : NOP ; Math keys are keys in row 2-4 except [<f>], [<g>], [EEX] and [*]	User interface			ON
fF4	MNUp1 	Setting (pgm)	Menu opens on p1	Switch on menu opens on p1	User interface	MNUp1	MNUp1 	ON
fF5	MyMb 	Setting	MyMenu shown	Switch on MyMenu shown ; not programmable - in PEM, use flag MyMb ; Info : MyMb and HOMEb are linked (both cannot be ON at the same time ; applies when all menus are exited using EXIT	Customisation	MyMb	MyMb 	ON
fF6	HOMEb 	Setting	HOME menu shown	Switch on HOME menu shown ; not programmable - in PEM, use flag HOMEb ; Info : HOMEb and MyMb are linked (both cannot be ON at the same time ; applies when all menus are exited using EXIT	Customisation	HOMEb	HOMEb 	OFF
gF1	F.14 	Setting (pgm)	Function keys skip f- and g-shift	Longpress control : Function keys skip f- and g-shift ; Info : 1. primaryNM : unshifted ; 4. longestpress : NOP	User interface			OFF
gF2	F.124 	Setting (pgm)	Function keys skip g-shift	Longpress control : Function keys skip g-shift ; Info : 1. primaryNM : unshifted ; 2. longpress : f-shift ; 4. longestpress : NOP	User interface			ON
gF3	F.1234 	Setting (pgm)	Function keys do full cycle	Longpress control : Function keys do full cycle ; Info : 1. primaryNM : unshifted ; 2. longpress : f-shift ; 3. longerpress : g-shift ; 4. longestpress : NOP	User interface			OFF
gF4	KEY.LP 	Setting	Longpress f and g shortcuts	Switch on longpress shortcuts for f-shift and g-shift keys ; not programmable - in PEM, use flag KEY.LP ; Info : KEY.LP pertains to R47v0 f/g layout and R47v2 f/g layout only and also enables longpress assignment to f-shift and g-shift keys	User interface	KEY.LP	KEY.LP 	ON
gF5	MyMf 	Setting	MyMenu f/g shortcut	Switch on MyMenu activated by triple and longerpress f/g-shift ; not programmable - in PEM, use flag MyMf ; Info : MyMf and HOMEf are linked (both cannot be ON at the same time ; MyMf pertains to layouts containing key [f/g] only and also enables longerpress assignment to this key	Customisation	MyMf	MyMf 	OFF
gF6	HOMEf 	Setting	HOME menu f/g shortcut	Switch on HOME menu activated by triple and longerpress f/g-shift ; not programmable - in PEM, use flag HOMEf ; Info : HOMEf and MyMf are linked (both cannot be ON at the same time ; HOMEf pertains to layouts containing key [f/g] only and also enables longerpress assignment to this key	Customisation	HOMEf	HOMEf 	ON