

Key	Row	Column	Kind	Label	FullName	Description	Type
C47.41.11	4	1	Primary	ENTER	Enter	Enter input value to X (optionally also to Y) or push/duplicate value already in X to Y	Function
C47.41.12	4	1	f	COMPLEX	Complex	Convert to or from complex number (Info : a ENTER b COMPLEX returns a+bi or a∠b (using b angle tag or ADM) ; COMPLEX returns Y : a, X : b)	Function
C47.41.13	4	1	g	CPX	Complex	Complex functions	MENU
C47.41.31	4	1	alpha	ENTER	Enter	Enter input value to X (optionally also to Y) or push/duplicate value already in X to Y	Function
C47.41.32	4	1	alpha f	X.EDIT	X.EDIT	Append contents of register X to alpha and enter alpha input mode (AIM)	Function
C47.41.33	4	1	alpha g	αPARSE	Alpha parse	Parse alpha input for numeric content (in development)	Function (strike)
C47.42.11	4	2	Primary	↔	Swap X and Y	Swap register X and register Y	Function
C47.42.12	4	2	f	LASTx	Last X	Recall last X (register L)	Function
C47.42.13	4	2	g	STK	Stack	Stack functions	MENU
C47.42.31	4	2	alpha	M	M	Character M	Character
C47.42.32	4	2	alpha f	m	m lowercase	Character m	Character
C47.42.33	4	2	alpha g	↔	Exchange	Character ↔ (Code : 8644)	Character
C47.43.11	4	3	Primary	+/-	Change sign	Change sign	Function
C47.43.12	4	3	f	MODE	Mode settings	System (mode) settings with status indication and modification	MENU
C47.43.13	4	3	g	TRG	Trigonometry	Trigonometry and hyperbolic functions	MENU (47)
C47.43.31	4	3	alpha	N	N	Character N	Character
C47.43.32	4	3	alpha f	n	n lowercase	Character n	Character
C47.43.33	4	3	alpha g	±	Plus-minus	Character ± (Code : 177)	Character
C47.44.11	4	4	Primary	[E]	Enter exponent	Enter exponent	Function
C47.44.12	4	4	f	DISP	Display settings	Display settings	MENU
C47.44.13	4	4	g	EXP	Exponential	Exponential functions	MENU
C47.44.31	4	4	alpha	0	0	Character 0	Character
C47.44.32	4	4	alpha f	o	o lowercase	Character o	Character
C47.44.33	4	4	alpha g	<E>	E (outline)	Character E (Hidden : gShiftedAIM (Numlock) [E] (C47.44.11) ; Code : 8307)	Character
C47.45.11	4	5	Primary	↵	Backspace	Backspace (Clear NIM) (Moniker : BKSPC)	Function (nonpgm)
C47.45.12	4	5	f	↶	Undo	Restore complete stack and LASTx register	Function
C47.45.13	4	5	g	CLR	Clear	Clear flags, programs, registers, stacks, variables and reset calculator	MENU
C47.45.31	4	5	alpha	↵	Backspace	Backspace (Clear NIM) (Moniker : BKSPC)	Function (nonpgm)
C47.45.32	4	5	alpha f	CLA	Clear alpha	Clear alphabetic input (Hidden : Longpress AIM ↵ (C47.45.34))	Function
C47.45.33	4	5	alpha g	CLA	Clear alpha	Clear alphabetic input (Hidden : Longpress AIM ↵ (C47.45.34))	Function
C47.46.11	4	6					
C47.46.12	4	6					
C47.46.13	4	6					
C47.46.31	4	6					
C47.46.32	4	6					
C47.46.33	4	6					