

CFLG	Configuration flags MENU (item, nonpgm) - cat : SYS.FL	Activates menu for setting system flags using FF (Flip flag) function ; displays menu SYS.FL	Category: Settings File: C47_Menu_CFG...
-------------	--	--	---

line scrolling indicator : A V

Menu	CFLG	1	2	3	4	5	6
3	g-shift	αCAP []					
2	f-shift	USB []	USER []	VMDISP []	WRPEDG []	WRPEND []	YMD [•]
1	unshifted	SLOW []	SOLVING []	SPCRES [•]	SSIZE8 [•]	TDM24 [•]	TRACE []
Page	5	F1	F2	F3	F4	F5	F6

Info Type characters 1-2 to search ; If SYS.FL is accessed from CAT.MENUS, soft buttons return flag status, otherwise toggle flag status

CFLG	Page 5	Button label (complete)	Full name	Description (extended)	Type	Flag name	Additional information	Catalog	Default	Status
F1		SLOW	Slow mode	SET for slow mode ; CLEAR for slow mode inactive	Flag	SLOW	Info : Slow mode limits battery drain		CLEAR	Checkbox
F2		SOLVING	Solving	SET for solver running ; CLEAR for solver not running	Flag (system)	SOLVING			CLEAR	System
F3		SPCRES	Special results	SET for special results ; CLEAR for special results inactive	Flag	SPCRES	Info : Special results are: infinity (∞) and not-a-number (NaN), an error will not occur for such events when SPCRES is SET		SET	Checkbox
F4		SSIZE8	Stack Size 8	SET for 8 register stack ; CLEAR for 4 register stack	Flag	SSIZE8	SBI : 8 ; 4 ; Info : SBI depends on SBus		SET	Checkbox
F5		TDM24	Time display 24h	SET for 24h time display ; CLEAR for 12h time display	Flag	TDM24	SBI : HH:MMam/pm ; HH24:MM ; Format : HH:MMam/pm ; HH24:MM		SET	Checkbox
F6		TRACE	Tracing	SET for printing in trace mode ; CLEAR for printing in normal mode	Flag	TRACE			CLEAR	Checkbox

fShifted F1	USB	USB Power	SET for calculator running on USB power ; CLEAR for calculator running on battery power	Flag (system)	USB	SBI : ψ			CLEAR	System
fShifted F2	USER	USER mode	SET for user mode ; CLEAR for user mode inactive	Flag	USER	SBI : U			CLEAR	Checkbox
fShifted F3	VMDISP	Variable Menu Displayed	SET for variable menu displayed ; CLEAR for variable menu displayed inactive	Flag (system)	VMDISP				CLEAR	System
fShifted F4	WRPEDG	Wrap edge	SET for wrap edge ; CLEAR for wrap edge inactive	Flag (system)	WRPEDG				CLEAR	System
fShifted F5	WRPEND	Wrap end	SET for wrap end ; CLEAR for wrap end inactive	Flag (system)	WRPEND				CLEAR	System
fShifted F6	YMD	Year-month-day	Set for YYYY-MM-DD display mode ; CLEAR for YYYY-MM-DD display mode inactive	Flag (system)	YMD	SBI : YYYY-MM-DD ; Format : YYYY-MM-DD			SET	System

gShifted F1	αCAP	Alpha capslock	SET for alpha capslock ; CLEAR for alpha capslock inactive	Flag (system)	CAPS	SBI : A ; a			CLEAR	System
gShifted F2	<empty>									
gShifted F3	<empty>									
gShifted F4	<empty>									
gShifted F5	<empty>									
gShifted F6	<empty>									