

| | | | |
|-------------|------------------------------------|------------------|--------------------|
| DISP | Display settings MENU - cat : DISP | Display settings | Category: Settings |
|-------------|------------------------------------|------------------|--------------------|

page scrolling indicator : ▲ ▼

| Menu | DISP | 1 | 2 | 3 | 4 | 5 | 6 |
|------|----------|--------------------|---------|--------------------|----------------------|----------|-----------|
| 3 | gShifted | | | | | | |
| 2 | fShifted | IPART _⌵ | RADIX. | FPART _⌵ | TDISP ₀ | RECT (•) | POLAR () |
| 1 | primary | FIX () | SCI () | ENG () | ALL ₃ (•) | SIG () | UNIT () |
| Page | 1 | F1 | F2 | F3 | F4 | F5 | F6 |

| | |
|----------|--------------------------|
| Ref page | Number format ; Regional |
|----------|--------------------------|

| DISP | Page 1 | | | | | | | | |
|-------|-------------------------|-----------------------------|--|---------------|-----------|------------------------------|----------------------|---------|-------------|
| F-key | Button label (complete) | Full name | Extended description | Type | Flag name | Additional information | Catalog | Default | Status |
| F1 | FIX | Fixed notation | Set numeric display mode to FIXed notation with nn+1 digits | Setting (pgm) | <no flag> | TAM : FIX __ TamNonReg menu | FIX () | OFF | Radiobutton |
| F2 | SCI | Scientific notation | Set numeric display mode to SCientific notation with nn+1 digits | Setting (pgm) | <no flag> | TAM : SCI __ TamNonReg menu | SCI () | OFF | Radiobutton |
| F3 | ENG | Engineering notation | Set numeric display mode to ENgineering notation with nn+1 digits | Setting (pgm) | <no flag> | TAM : ENG __ TamNonReg menu | ENG () | OFF | Radiobutton |
| F4 | ALL | All digits notation | Set numeric display mode to ALL digits notation ; display all digits as far as possible with max. nn decimal zeros | Setting (pgm) | <no flag> | TAM : ALL __ TamNonReg menu | ALL ₃ (•) | 3 | Radiobutton |
| F5 | SIG | Significant digits notation | Set numeric display mode to SIGNificant notation with nn+1 digits ; switching over to scientific or engineering notation when number of rounded trailing zeros exceeds group size (IPGRP) | Setting (pgm) | <no flag> | TAM : SIG __ TamNonReg menu | SIG () | OFF | Radiobutton |
| F6 | UNIT | Unit (prefix) notation | Set numeric display mode to UNIT nn+1 digits ; setting for showing all or limited set of prefixes: PFX.All (display using prefix also available from HOME for numeric entry: p - n - μ - m - k - M - G - T for pico, nano, micro, milli, kilo, Giga, Tera) | Setting (pgm) | <no flag> | TAM : UNIT __ TamNonReg menu | UNIT () | OFF | Radiobutton |

| | | | | | | | | | |
|-------------|--------------------|---------------------|--|---------------|-----------|---|--------------------|-----|-------------|
| fShifted F1 | IPART _⌵ | Select IP separator | Select integer part separator ; showing current separator ; symbol ø for no separator | MENU (item) | | CAT.MENUS : IPART | | | |
| fShifted F2 | RADIX. | Select radix | Select radix ; showing current radix | MENU (item) | | CAT.MENUS : RADIX | | | |
| fShifted F3 | FPART _⌵ | Select FP separator | Select fractional part separator ; showing current separator ; symbol ø for no separator | MENU (item) | | CAT.MENUS : FPART | | | |
| fShifted F4 | TDISP | Time display format | Set time display format: 0 = full ; 1,2 = hours/minutes ; 3 = hours/minutes/seconds ; 4,5,6 = 1,2,3 decimal places for the seconds | Setting | <no flag> | TAM : TDISP _ TamNonReg menu | TDISP ₀ | 0 | Value |
| fShifted F5 | RECT | Rectangular | Rectangular display of complex numbers (internal value is RECT) | Setting (pgm) | POLAR | SBI : L ; Shortcut : FF X (TAM) ; Info : SBI depends on SBcpx | RECT (•) | ON | Radiobutton |
| fShifted F6 | POLAR | Polar | Polar representation of complex numbers (internal value is RECT) | Setting (pgm) | POLAR | SBI : O ; Shortcut : FF X (TAM) ; Info : SBI depends on SBcpx | POLAR () | OFF | Radiobutton |

| | | | | | | | | | |
|-------------|---------|--|--|--|--|--|--|--|--|
| gShifted F1 | <empty> | | | | | | | | |
| gShifted F2 | <empty> | | | | | | | | |
| gShifted F3 | <empty> | | | | | | | | |
| gShifted F4 | <empty> | | | | | | | | |
| gShifted F5 | <empty> | | | | | | | | |
| gShifted F6 | <empty> | | | | | | | | |