

IPART	Select IP separator MENU - cat : IPART	Select integer part separator	Category: Settings
--------------	--	-------------------------------	--------------------

Menu	IPART	1	2	3	4	5	6
3	gShifted	IPGRP ₃	IPGRP ₁₀	IPGRP1x ₀		NSPC _␣ ()	
2	fShifted	WPER. ()	WCOM, ()	WDOT• ()	WTICK' ()	WSPC _{␣␣} ()	UNDR_ ()
1	primary	PER. ()	COM, ()	DOT• ()	TICK' ()	SPC _␣ (•)	NONE ()
Page	1	F1	F2	F3	F4	F5	F6

IPART	Page 1	F-key	Button label	Full name	Extended description	Type	Flag name	Additional information	Catalog	Default	Status
F1			PER.	IP separator period	Set integer part separator to period	Setting (pgm)	<no flag>		IPER. ()	OFF	Radiobutton
F2			COM,	IP separator comma	Set integer part separator to comma	Setting (pgm)	<no flag>		ICOM, ()	OFF	Radiobutton
F3			DOT•	IP separator dot	Set integer part separator to dot	Setting (pgm)	<no flag>		IDOT• ()	OFF	Radiobutton
F4			TICK'	IP separator narrow tick	Set integer part separator to narrow tick	Setting (pgm)	<no flag>		ITICK' ()	OFF	Radiobutton
F5			SPC _␣	IP separator space	Set integer part separator to space	Setting (pgm)	<no flag>		ISPC _␣ (•)	ON	Radiobutton
F6			NONE	No IP separator	No integer part separator	Setting (pgm)	<no flag>	Info : Menu shows symbol ø	INONE ()	OFF	Radiobutton

fShifted F1	WPER.	IP separator wide period	Set integer part separator to wide period	Setting (pgm)	<no flag>		IWPER. ()	OFF	Radiobutton
fShifted F2	WCOM,	IP separator wide comma	Set integer part separator to wide comma	Setting (pgm)	<no flag>		IWCOM, ()	OFF	Radiobutton
fShifted F3	WDOT•	IP separator wide dot	Set integer part separator to wide dot	Setting (pgm)	<no flag>		IWDOT• ()	OFF	Radiobutton
fShifted F4	WTICK'	IP separator tick	Set integer part separator to tick	Setting (pgm)	<no flag>		IWTICK' ()	OFF	Radiobutton
fShifted F5	WSPC _{␣␣}	IP separator double space	Set integer part separator to double space	Setting (pgm)	<no flag>		IWSPC _{␣␣} ()	OFF	Radiobutton
fShifted F6	UNDR_	IP separator underscore	Set integer part separator to underscore	Setting (pgm)	<no flag>		IUNDR_ ()	OFF	Radiobutton

gShifted F1	IPGRP	IP group size	Set integer part group size (2..9) ; not for SCI or ENG notation	Setting (pgm)	<no flag>	TAM : IPGRP _ TamNonReg menu	IPGRP ₃	3	Value
gShifted F2	IPGRP1	IP first group size	Set integer part first group size ; parameter 0 means follow IPGRP	Setting (pgm)	<no flag>	TAM : IPGRP1 _ TamNonReg menu	IPGRP ₁₀	0	Value
gShifted F3	IPGRP1x	IP first group extension	Extend first group to allow one additional digit up to maximum specified by parameter	Setting (pgm)	<no flag>	TAM : IPGRP1x _ TamNonReg menu	IPGRP1x ₀	0	Value
gShifted F4	<empty>								
gShifted F5	NSPC _␣	IP separator narrow space	Set integer part separator to narrow space	Setting (pgm)	<no flag>		INSPC _␣ ()	OFF	Radiobutton
gShifted F6	<empty>								