

MODE	Mode settings MENU - cat : MODE	System (mode) settings with status indication and modification	Category: Settings
-------------	---------------------------------	----------------------------------------------------------------	--------------------

page scrolling indicator : ▲ ▼

Menu	MODE	1	2	3	4	5	6
3	gShifted				F.14 ()	F.124 (•)	F.1234 ()
2	fShifted	fg.OFF ()	fg.LIM ()	fg.FUL (•)	M.14 ()	M.124 ()	M.1234 (•)
1	primary	MyM [•]	HOME []	HOME.3 [•]	g.2Tp [•]	SH.4s [•]	S.RESET
Page	3	F1	F2	F3	F4	F5	F6

--	--	--	--	--	--	--	--

MODE	Page 3								
F-key	Button label (complete)	Full name	Extended description	Type	Flag name	Additional information	Catalog	Default	Status
F1	MyM	MyMenu shown	Base MyMenu shown (when all menus are exited using EXIT)	Setting	<no flag>		MyM [•]	ON	Checkbox
F2	HOME	HOME menu shown	HOME menu shown (when all menus are exited using EXIT)	Setting	<no flag>		_HOME []	OFF	Checkbox
F3	HOME.3	Home menu fff shortcut	HOME menu activated by triple shift	Setting	<no flag>		HOME.3 [•]	ON	Checkbox
F4	g.2Tp	Function keys g-shortcut	Allow double tapping the FN-keys for a g-function	Setting	<no flag>	Info : Blocked for (navigation) arrows in editors	g.2Tp [•]	ON	Checkbox
F5	SH.4s	Shift time-out 4s	Set shift to time out after 4 seconds	Setting	<no flag>		SH.4s [•]	ON	Checkbox
F6	S.RESET	Reset f/g timers	Safe reset, then toggle ON/OFF all accessibility related options: HOME.3 [•] ; g.2Tp [•] ; SH.4s [•] ; fg.FUL (•)	Command			S.RESET		

fShifted F1	fg.OFF	Menu fg-highlighting Off	Do not show horizontal f- and g-lines indicating the state of the f- or g-shift in menu	Setting	<no flag>		fg.OFF ()	OFF	Radiobutton
fShifted F2	fg.LIM	Menu fg-highlighting Limited	Show limited horizontal f- and g-lines indicating the state of the f- or g-shift in menu	Setting	<no flag>		fg.LIM ()	OFF	Radiobutton
fShifted F3	fg.FUL	Menu fg-highlighting Full	Show full horizontal f- and g-lines indicating the state of the f- or g-shift in menu	Setting	<no flag>		fg.FUL (•)	ON	Radiobutton
fShifted F4	M.14	Math keys skip fg	Longpress control : skip f and g Math keys longpress cycle	Setting	<no flag>			OFF	Radiobutton
fShifted F5	M.124	Math keys skip g	Longpress control : skip g Math keys longpress cycle	Setting	<no flag>			OFF	Radiobutton
fShifted F6	M.1234	Math keys full cycle	Longpress control : full Math keys longpress cycle	Setting	<no flag>			ON	Radiobutton

gShifted F1	<empty>								
gShifted F2	<empty>								
gShifted F3	<empty>								
gShifted F4	F.14	Function keys skip fg	Longpress control : skip f and g Function key longpress cycle	Setting	<no flag>			OFF	Radiobutton
gShifted F5	F.124	Function keys skip g	Longpress control : skip g Function key longpress cycle	Setting	<no flag>			ON	Radiobutton
gShifted F6	F.1234	Function keys full cycle	Longpress control : full Function key longpress cycle	Setting	<no flag>			OFF	Radiobutton