

STK	Stack MENU - cat : STK	Stack functions	Category: Stack
------------	------------------------	-----------------	-----------------

Menu	STK	1	2	3	4	5	6
3	gShifted						
2	fShifted	R↑	x↔	y↔	z↔	t↔	↔
1	primary	R↓	DROP↓	DROPy	LASTx	FILL	CLSTK
Page	1	F1	F2	F3	F4	F5	F6

--	--	--	--	--	--	--	--

STK	Page 1								
F-key	Button label	Full name	Extended description	Type	Flag name	Additional information	Catalog	Default	Status
F1	R↓	Roll down	Roll down stack	Command			R↓		
F2	DROP↓	Drop	Drop one stack level	Command		Hidden : Double ⇔ (C47.45.15)	DROP		
F3	DROPy	Drop Y	Drop Y from stack	Command			DROPy		
F4	LASTx	Last X	Recall last X (register L)	Command			LASTx		
F5	FILL	Fill stack	Fill stack with value in the X-register	Command			FILL		
F6	CLSTK	Clear stack	Clear all stack data	Command		Hidden : Longpress ⇔ (C47.45.14)	CLSTK		

fShifted F1	R↑	Roll up	Roll up stack	Command			R↑		
fShifted F2	x↔	Swap X	Swap X and register	Command		TAM : x↔ __ Tam menu	x↔		
fShifted F3	y↔	Swap Y	Swap Y and register	Command		TAM : y↔ __ Tam menu	y↔		
fShifted F4	z↔	Swap Z	Swap Z and register	Command		TAM : z↔ __ Tam menu	z↔		
fShifted F5	t↔	Swap T	Swap T and register	Command		TAM : t↔ __ Tam menu	t↔		
fShifted F6	↔	Shuffle stack	Shuffle stack: replace X Y Z T by selection of X Y Z T	Command		TAM : ↔ ____ TamShuffle menu	↔		

gShifted F1	<empty>								
gShifted F2	<empty>								
gShifted F3	<empty>								
gShifted F4	<empty>								
gShifted F5	<empty>								
gShifted F6	<empty>								