

MyM	MyMenu					
g-shift						
f-shift						
unshifted	<i>i</i>	<i>i</i> ⓪	x!	xy	10 ^x	e ^x
Page 6	F1	F2	F3	F4	F5	F6

Prev menu https://47calc.com/doc/C47/Menus/C47_Menu_MyMenu_page_5.pdf

Next menu https://47calc.com/doc/C47/Menus/C47_Menu_MyMenu_page_7.pdf

Level	Label	Type	FullName	Extended description	Category	Flag	Catalog	Default
Menu p6	MyM	MENU	MyMenu	User menu presenting a ribbon to quickly access user selected functions (and menus) ; all buttons are user assignable ('riveted' look) ; set by RIBBONS ; reset using MyM.R ; default ribbon M.C47 ; Shortcut : PEM longer [EXIT] ; longpress [EXIT] ; NIM long [EXIT] ; during assignment, pressing USER (f[2]) opens MyMenu ; Info : ribbons are documenten on page 1 : M.CPX ; 2 : M.ENG ; 3 : M.FIN ; 4 : M.SAV ; 5 : M.C47 ; 6 : M.R47 ; 7 : M.FIN+ ; 8 : M.SAV+	Customisation		MyMenu	
F1	i	Command	Complex number (rectangular notation)	Enter complex number (rectangular notation) whether RECT is set or not ; e.g. a i b ENTER results in a + b i ; Info : In NIM, works like CC with RECT set ; displayed according to flag CPX.j when in RECT mode	Complex numbers	CPX.j	op_ i	
F2	$i_{\odot}$	Command	Complex number (polar notation)	Enter complex number (polar notation) whether POLAR is set or not ; e.g. a $i_{\odot}$ b ENTER results in a $\times$ b (according to ADM) ; Info : In NIM, works like CC with POLAR set ; displayed according to flag CPX.j when in RECT mode	Complex numbers	CPX.j	op_ $i_{\odot}$	
F3	x!	Function (monadic)	Factorial x! or $\Gamma(x+1)$	For Long integers : x! ; for Reals : $\Gamma(x+1)$; Info : Max integer: 450 (up to 1000 digits accurate) ; max real : 2123.549 956 662 463 236 31 ; integers > max are converted to reals	Mathematics		x!	
F4	$\sqrt[y]{x}$	Function (dyadic)	xth root	Xth root of Y	Mathematics		$\sqrt[y]{x}$	
F5	10 ^x	Function (monadic)	10 to the power x	Raise 10 to the power in the X-register	Mathematics		10 ^x	
F6	e ^x	Function (monadic)	e to the power x	Raise e to the power in the X-register	Mathematics		e ^x	
fF1								
fF2								
fF3								
fF4								
fF5								
fF6								
gF1								
gF2								
gF3								
gF4								
gF5								
gF6								